

SONIFEX

RB-LC3

3 Way Light/Power Controller

Catalogue





RB-LC3 3 Way Light/Power Controller



Category: Power Controllers.

Product Function: To switch mains power to 3 x IEC outlets for mains voltage signal lamps.

Typical Applications: Controlling radio studio On-Air, Mic-Live and Telephone signal lamps.

Features:

- GPI to control switching of 3 IEC outlets.
- Telephony input for 'Call Ringing' displays.
- Flash rate control.

The RB-LC3 is a triple output switching unit for controlling external mains indicators, primarily studio status lights for broadcasting applications, such as On-Air, Mic-Live and Rehearsal/Live lights.

Each output can be individually controlled by one of three remote inputs (pulled high,

or low), by a telephony input (when ringing, or off-hook, or both), or a combination of two inputs (to control two outputs, e.g. for Rehearsal/Live situations). The type of control is set using the 12 way DIP switch (4 switches for each output, allowing 16 different settings).

All connections are on the rear panel. The three IEC outputs are controlled by zero-cross point drivers. When an output is activated, the A.C. voltage level at that output will be equal to the mains input voltage used to power the unit.

External control of the switched mains outputs is via the 15 way D-type plug connector.

The telephone line input and handset output are via two RJ11-4 type connectors. The telephone connections are wired pin to pin from line to handset except when the remote 'Ring Mute' control input is asserted. In this case the ring signal to the handset is muted.

The status of the telephone line is continually monitored so that handset

ringing and off-hook conditions can be indicated.

A pre-set potentiometer on the rear panel controls the flash rate of the output when the appropriate mode is selected. Neon indicators on each power socket show the status of the mains output.

Specification For RB-LC3

Audio Specification

| Connections | |
|------------------------------|---|
| Mains Input: | Non-filtered IEC, 110V-240V auto-adjusting, fused, 6W maximum |
| Mains Outputs: | 3 x Non-filtered IEC plugs, 1A fused |
| Fuse Rating (Mains Outputs): | 3 x Anti-surge fuse 1A 20 x 5mm |
| Telephone: | 2 x RJ11-4 sockets |
| Control Inputs & Outputs: | 15 way D-type plug Inputs: 0V- 5V DC Outputs: Open collector 20mA sink capability |

Equipment Type

| | |
|---------|------------------------------|
| RB-LC3: | 3 way light/power controller |
|---------|------------------------------|

Physical Specification

| | |
|---------------------|---|
| Dimensions | 28cm (W) x 10.8cm (D) x 4.2cm (H) (1U) |
| (Raw): | 11" (W) x 4.3" (D) x 1.7" (H) (1U) |
| Dimensions (Boxed): | 36cm (W) x 20.5cm (D) x 6cm (H) 14.2" (W) x 8" (D) x 2.4" (H) |
| Weight: | Nett: 1.00kg Gross: 1.45kg Nett: 2.2lbs Gross: 3.2lbs |



SONIFEX

www.sonifex.co.uk

UK Office:

Sonifex Ltd

61 Station Road, Irthlingborough,

Northants, NN9 5QE, UK

Tel: +44 (0) 1933 650700

Fax: +44 (0) 1933 650726

Email: sales@sonifex.co.uk

Australian Office:

Sonifex Pty Ltd

12/6 Leighton Place,

Hornsby NSW 2077, Australia

Tel: +61 (2) 9987 0499

Fax: +61 (2) 9476 4950

Email: sales@sonifex.com.au