

AVN-PXH12 Ember+ Reference

Generated from AVN-PXH12.xml on 2026-10-05 10:55:20 +01:00

293

Parameters

1

Functions

1

Matrices

157

Nodes

Parameters

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.1.1	root / identity / product	String [3]	Read [1]	AVN-PXH12 UTF8	
1.1.2	root / identity / company	String [3]	Read [1]	Sonifex Ltd. UTF8	
1.1.3	root / identity / serial	String [3]	Read [1]	0141597 UTF8	
1.1.4	root / identity / version	String [3]	Read [1]	3.2.2603 UTF8	
1.3.1	root / network / friendly_name	String [3]	Read / Write [3]	AVN-PXH12-0141597 UTF8	
1.3.2.1	root / network / eth0 / mode	Integer [1]	Read / Write [3]	2 INTEGER	Allowed values 0 = disabled 1 = static 2 = dynamic
1.3.2.2	root / network / eth0 / ip_address	String [3]	Read / Write [3]	192.168.0.100 UTF8	
1.3.2.3	root / network / eth0 / netmask	String [3]	Read / Write [3]	255.255.255.0 UTF8	
1.3.2.4	root / network / eth0 / gateway	String [3]	Read / Write [3]	0.0.0.0 UTF8	
1.3.2.5	root / network / eth0 / mac_address	String [3]	Read [1]	D0:A4:B1:00:3A:75 UTF8	
1.3.3.1	root / network / eth1 / mode	Integer [1]	Read / Write [3]	2 INTEGER	Allowed values 0 = disabled 1 = static 2 = dynamic
1.3.3.2	root / network / eth1 / ip_address	String [3]	Read / Write [3]	192.168.1.100 UTF8	
1.3.3.3	root / network / eth1 / netmask	String [3]	Read / Write [3]	255.255.255.0 UTF8	
1.3.3.4	root / network / eth1 / gateway	String [3]	Read / Write [3]	0.0.0.0 UTF8	
1.3.3.5	root / network / eth1 / mac_address	String [3]	Read [1]	D0:A4:B1:00:3A:76 UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.1.1.0	root / audio routing / labels / targets / t-0	String [3]	Read / Write [3]	Mixer Source 1:Norm 1 UTF8	
1.4.1.1.1	root / audio routing / labels / targets / t-1	String [3]	Read / Write [3]	Mixer Source 1:Norm 2 UTF8	
1.4.1.1.2	root / audio routing / labels / targets / t-2	String [3]	Read / Write [3]	Mixer Source 1:Alt 1 UTF8	
1.4.1.1.3	root / audio routing / labels / targets / t-3	String [3]	Read / Write [3]	Mixer Source 1:Alt 2 UTF8	
1.4.1.1.4	root / audio routing / labels / targets / t-4	String [3]	Read / Write [3]	Mixer Source 2:Norm 1 UTF8	
1.4.1.1.5	root / audio routing / labels / targets / t-5	String [3]	Read / Write [3]	Mixer Source 2:Norm 2 UTF8	
1.4.1.1.6	root / audio routing / labels / targets / t-6	String [3]	Read / Write [3]	Mixer Source 2:Alt 1 UTF8	
1.4.1.1.7	root / audio routing / labels / targets / t-7	String [3]	Read / Write [3]	Mixer Source 2:Alt 2 UTF8	
1.4.1.1.8	root / audio routing / labels / targets / t-8	String [3]	Read / Write [3]	Mixer Source 3:Norm 1 UTF8	
1.4.1.1.9	root / audio routing / labels / targets / t-9	String [3]	Read / Write [3]	Mixer Source 3:Norm 2 UTF8	
1.4.1.1.10	root / audio routing / labels / targets / t-10	String [3]	Read / Write [3]	Mixer Source 3:Alt 1 UTF8	
1.4.1.1.11	root / audio routing / labels / targets / t-11	String [3]	Read / Write [3]	Mixer Source 3:Alt 2 UTF8	
1.4.1.1.12	root / audio routing / labels / targets / t-12	String [3]	Read / Write [3]	Mixer Source 4:Norm 1 UTF8	
1.4.1.1.13	root / audio routing / labels / targets / t-13	String [3]	Read / Write [3]	Mixer Source 4:Norm 2 UTF8	
1.4.1.1.14	root / audio routing / labels / targets / t-14	String [3]	Read / Write [3]	Mixer Source 4:Alt 1 UTF8	
1.4.1.1.15	root / audio routing / labels / targets / t-15	String [3]	Read / Write [3]	Mixer Source 4:Alt 2 UTF8	
1.4.1.1.16	root / audio routing / labels / targets / t-16	String [3]	Read / Write [3]	Mixer Source 5:Norm 1 UTF8	
1.4.1.1.17	root / audio routing / labels / targets / t-17	String [3]	Read / Write [3]	Mixer Source 5:Norm 2 UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.1.1.18	root / audio routing / labels / targets / t-18	String [3]	Read / Write [3]	Mixer Source 5:Alt 1 UTF8	
1.4.1.1.19	root / audio routing / labels / targets / t-19	String [3]	Read / Write [3]	Mixer Source 5:Alt 2 UTF8	
1.4.1.1.20	root / audio routing / labels / targets / t-20	String [3]	Read / Write [3]	Mixer Source 6:Norm 1 UTF8	
1.4.1.1.21	root / audio routing / labels / targets / t-21	String [3]	Read / Write [3]	Mixer Source 6:Norm 2 UTF8	
1.4.1.1.22	root / audio routing / labels / targets / t-22	String [3]	Read / Write [3]	Mixer Source 6:Alt 1 UTF8	
1.4.1.1.23	root / audio routing / labels / targets / t-23	String [3]	Read / Write [3]	Mixer Source 6:Alt 2 UTF8	
1.4.1.1.24	root / audio routing / labels / targets / t-24	String [3]	Read / Write [3]	Mixer Source 7:Norm 1 UTF8	
1.4.1.1.25	root / audio routing / labels / targets / t-25	String [3]	Read / Write [3]	Mixer Source 7:Norm 2 UTF8	
1.4.1.1.26	root / audio routing / labels / targets / t-26	String [3]	Read / Write [3]	Mixer Source 7:Alt 1 UTF8	
1.4.1.1.27	root / audio routing / labels / targets / t-27	String [3]	Read / Write [3]	Mixer Source 7:Alt 2 UTF8	
1.4.1.1.28	root / audio routing / labels / targets / t-28	String [3]	Read / Write [3]	Mixer Source 8:Norm 1 UTF8	
1.4.1.1.29	root / audio routing / labels / targets / t-29	String [3]	Read / Write [3]	Mixer Source 8:Norm 2 UTF8	
1.4.1.1.30	root / audio routing / labels / targets / t-30	String [3]	Read / Write [3]	Mixer Source 8:Alt 1 UTF8	
1.4.1.1.31	root / audio routing / labels / targets / t-31	String [3]	Read / Write [3]	Mixer Source 8:Alt 2 UTF8	
1.4.1.1.32	root / audio routing / labels / targets / t-32	String [3]	Read / Write [3]	Mixer Source 9:Norm 1 UTF8	
1.4.1.1.33	root / audio routing / labels / targets / t-33	String [3]	Read / Write [3]	Mixer Source 9:Norm 2 UTF8	
1.4.1.1.34	root / audio routing / labels / targets / t-34	String [3]	Read / Write [3]	Mixer Source 9:Alt 1 UTF8	
1.4.1.1.35	root / audio routing / labels / targets / t-35	String [3]	Read / Write [3]	Mixer Source 9:Alt 2 UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.1.1.36	root / audio routing / labels / targets / t-36	String [3]	Read / Write [3]	Mixer Source 10:Norm 1 UTF8	
1.4.1.1.37	root / audio routing / labels / targets / t-37	String [3]	Read / Write [3]	Mixer Source 10:Norm 2 UTF8	
1.4.1.1.38	root / audio routing / labels / targets / t-38	String [3]	Read / Write [3]	Mixer Source 10:Alt 1 UTF8	
1.4.1.1.39	root / audio routing / labels / targets / t-39	String [3]	Read / Write [3]	Mixer Source 10:Alt 2 UTF8	
1.4.1.1.40	root / audio routing / labels / targets / t-40	String [3]	Read / Write [3]	Mixer Source 11:Norm 1 UTF8	
1.4.1.1.41	root / audio routing / labels / targets / t-41	String [3]	Read / Write [3]	Mixer Source 11:Norm 2 UTF8	
1.4.1.1.42	root / audio routing / labels / targets / t-42	String [3]	Read / Write [3]	Mixer Source 11:Alt 1 UTF8	
1.4.1.1.43	root / audio routing / labels / targets / t-43	String [3]	Read / Write [3]	Mixer Source 11:Alt 2 UTF8	
1.4.1.1.44	root / audio routing / labels / targets / t-44	String [3]	Read / Write [3]	Mixer Source 12:Norm 1 UTF8	
1.4.1.1.45	root / audio routing / labels / targets / t-45	String [3]	Read / Write [3]	Mixer Source 12:Norm 2 UTF8	
1.4.1.1.46	root / audio routing / labels / targets / t-46	String [3]	Read / Write [3]	Mixer Source 12:Alt 1 UTF8	
1.4.1.1.47	root / audio routing / labels / targets / t-47	String [3]	Read / Write [3]	Mixer Source 12:Alt 2 UTF8	
1.4.1.1.48	root / audio routing / labels / targets / t-48	String [3]	Read / Write [3]	XLR Output 1:CH 1 UTF8	
1.4.1.1.49	root / audio routing / labels / targets / t-49	String [3]	Read / Write [3]	XLR Output 2:CH 1 UTF8	
1.4.1.1.50	root / audio routing / labels / targets / t-50	String [3]	Read / Write [3]	XLR Output 3:CH 1 UTF8	
1.4.1.1.51	root / audio routing / labels / targets / t-51	String [3]	Read / Write [3]	LS Output UTF8	
1.4.1.2.0	root / audio routing / labels / sources / s-0	String [3]	Read / Write [3]	Mono Mixer Output:CH 1 UTF8	
1.4.1.2.1	root / audio routing / labels / sources / s-1	String [3]	Read / Write [3]	Stereo Mixer Output:CH 1 UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.1.2.2	root / audio routing / labels / sources / s-2	String [3]	Read / Write [3]	Stereo Mixer Output:CH 2 UTF8	
1.4.1.2.3	root / audio routing / labels / sources / s-3	String [3]	Read / Write [3]	Input 1 (Front):CH 1 UTF8	
1.4.1.2.4	root / audio routing / labels / sources / s-4	String [3]	Read / Write [3]	Input 1 (Front):CH 2 UTF8	
1.4.1.2.5	root / audio routing / labels / sources / s-5	String [3]	Read / Write [3]	Input 2 (Rear XLRs):CH 1 UTF8	
1.4.1.2.6	root / audio routing / labels / sources / s-6	String [3]	Read / Write [3]	Input 2 (Rear XLRs):CH 2 UTF8	
1.4.1.2.7	root / audio routing / labels / sources / s-7	String [3]	Read / Write [3]	Input 3 (Rear):CH 1 UTF8	
1.4.1.2.8	root / audio routing / labels / sources / s-8	String [3]	Read / Write [3]	Input 3 (Rear):CH 2 UTF8	
1.4.1.2.9	root / audio routing / labels / sources / s-9	String [3]	Read / Write [3]	Input 4 (Rear):CH 1 UTF8	
1.4.1.2.10	root / audio routing / labels / sources / s-10	String [3]	Read / Write [3]	Input 4 (Rear):CH 2 UTF8	
1.4.2.1.0.1	root / audio routing / parameters / targets / t-0 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.1.1	root / audio routing / parameters / targets / t-1 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.2.1	root / audio routing / parameters / targets / t-2 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.3.1	root / audio routing / parameters / targets / t-3 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.4.1	root / audio routing / parameters / targets / t-4 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.5.1	root / audio routing / parameters / targets / t-5 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.6.1	root / audio routing / parameters / targets / t-6 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.7.1	root / audio routing / parameters / targets / t-7 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.8.1	root / audio routing / parameters / targets / t-8 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.2.1.9.1	root / audio routing / parameters / targets / t-9 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.10.1	root / audio routing / parameters / targets / t-10 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.11.1	root / audio routing / parameters / targets / t-11 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.12.1	root / audio routing / parameters / targets / t-12 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.13.1	root / audio routing / parameters / targets / t-13 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.14.1	root / audio routing / parameters / targets / t-14 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.15.1	root / audio routing / parameters / targets / t-15 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.16.1	root / audio routing / parameters / targets / t-16 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.17.1	root / audio routing / parameters / targets / t-17 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.18.1	root / audio routing / parameters / targets / t-18 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.19.1	root / audio routing / parameters / targets / t-19 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.20.1	root / audio routing / parameters / targets / t-20 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.21.1	root / audio routing / parameters / targets / t-21 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.22.1	root / audio routing / parameters / targets / t-22 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.23.1	root / audio routing / parameters / targets / t-23 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.24.1	root / audio routing / parameters / targets / t-24 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.25.1	root / audio routing / parameters / targets / t-25 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.26.1	root / audio routing / parameters / targets / t-26 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.2.1.27.1	root / audio routing / parameters / targets / t-27 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.28.1	root / audio routing / parameters / targets / t-28 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.29.1	root / audio routing / parameters / targets / t-29 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.30.1	root / audio routing / parameters / targets / t-30 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.31.1	root / audio routing / parameters / targets / t-31 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.32.1	root / audio routing / parameters / targets / t-32 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.33.1	root / audio routing / parameters / targets / t-33 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.34.1	root / audio routing / parameters / targets / t-34 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.35.1	root / audio routing / parameters / targets / t-35 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.36.1	root / audio routing / parameters / targets / t-36 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.37.1	root / audio routing / parameters / targets / t-37 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.38.1	root / audio routing / parameters / targets / t-38 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.39.1	root / audio routing / parameters / targets / t-39 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.40.1	root / audio routing / parameters / targets / t-40 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.41.1	root / audio routing / parameters / targets / t-41 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.42.1	root / audio routing / parameters / targets / t-42 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.43.1	root / audio routing / parameters / targets / t-43 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.44.1	root / audio routing / parameters / targets / t-44 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.2.1.45.1	root / audio routing / parameters / targets / t-45 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.46.1	root / audio routing / parameters / targets / t-46 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.47.1	root / audio routing / parameters / targets / t-47 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.48.1	root / audio routing / parameters / targets / t-48 / line up	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = +18dBu = 0dBFS 1 = +22dBu = 0dBFS 2 = +24dBu = 0dBFS
1.4.2.1.48.2	root / audio routing / parameters / targets / t-48 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.49.1	root / audio routing / parameters / targets / t-49 / line up	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = +18dBu = 0dBFS 1 = +22dBu = 0dBFS 2 = +24dBu = 0dBFS
1.4.2.1.49.2	root / audio routing / parameters / targets / t-49 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.50.1	root / audio routing / parameters / targets / t-50 / line up	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = +18dBu = 0dBFS 1 = +22dBu = 0dBFS 2 = +24dBu = 0dBFS
1.4.2.1.50.2	root / audio routing / parameters / targets / t-50 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.1.51.1	root / audio routing / parameters / targets / t-51 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.3.1	root / audio routing / parameters / sources / s-3 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.4.1	root / audio routing / parameters / sources / s-4 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.5.1	root / audio routing / parameters / sources / s-5 / line up	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = +18dBu = 0dBFS 1 = +22dBu = 0dBFS 2 = +24dBu = 0dBFS
1.4.2.2.5.2	root / audio routing / parameters / sources / s-5 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.6.1	root / audio routing / parameters / sources / s-6 / line up	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = +18dBu = 0dBFS 1 = +22dBu = 0dBFS 2 = +24dBu = 0dBFS
1.4.2.2.6.2	root / audio routing / parameters / sources / s-6 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.4.2.2.7.1	root / audio routing / parameters / sources / s-7 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.8.1	root / audio routing / parameters / sources / s-8 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.9.1	root / audio routing / parameters / sources / s-9 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.4.2.2.10.1	root / audio routing / parameters / sources / s-10 / mute	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.1.1.1	root / gpio / physical / gpio 1 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.1.1.2	root / gpio / physical / gpio 1 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.1.1.3	root / gpio / physical / gpio 1 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.1.1.4	root / gpio / physical / gpio 1 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.1.1.5	root / gpio / physical / gpio 1 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.1.1.6	root / gpio / physical / gpio 1 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.1.2.1	root / gpio / physical / gpio 2 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.1.2.2	root / gpio / physical / gpio 2 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.1.2.3	root / gpio / physical / gpio 2 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.1.2.4	root / gpio / physical / gpio 2 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.1.2.5	root / gpio / physical / gpio 2 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.1.2.6	root / gpio / physical / gpio 2 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.1.3.1	root / gpio / physical / gpio 3 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.1.3.2	root / gpio / physical / gpio 3 / input functions	String [3]	Read / Write	UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
			[3]		
1.5.1.3.3	root / gpio / physical / gpio 3 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.3.4	root / gpio / physical / gpio 3 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.3.5	root / gpio / physical / gpio 3 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.3.6	root / gpio / physical / gpio 3 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.4.1	root / gpio / physical / gpio 4 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.4.2	root / gpio / physical / gpio 4 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.4.3	root / gpio / physical / gpio 4 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.4.4	root / gpio / physical / gpio 4 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.4.5	root / gpio / physical / gpio 4 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.4.6	root / gpio / physical / gpio 4 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.5.1	root / gpio / physical / gpio 5 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.5.2	root / gpio / physical / gpio 5 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.5.3	root / gpio / physical / gpio 5 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.5.4	root / gpio / physical / gpio 5 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.5.5	root / gpio / physical / gpio 5 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.5.6	root / gpio / physical / gpio 5 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.6.1	root / gpio / physical / gpio 6 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.1.6.2	root / gpio / physical / gpio 6 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.6.3	root / gpio / physical / gpio 6 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.6.4	root / gpio / physical / gpio 6 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.6.5	root / gpio / physical / gpio 6 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.6.6	root / gpio / physical / gpio 6 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.7.1	root / gpio / physical / gpio 7 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.7.2	root / gpio / physical / gpio 7 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.7.3	root / gpio / physical / gpio 7 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.7.4	root / gpio / physical / gpio 7 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.7.5	root / gpio / physical / gpio 7 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.7.6	root / gpio / physical / gpio 7 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.8.1	root / gpio / physical / gpio 8 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.8.2	root / gpio / physical / gpio 8 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.8.3	root / gpio / physical / gpio 8 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.8.4	root / gpio / physical / gpio 8 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.8.5	root / gpio / physical / gpio 8 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.8.6	root / gpio / physical / gpio 8 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.9.1	root / gpio / physical / gpio 9 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.1.9.2	root / gpio / physical / gpio 9 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.9.3	root / gpio / physical / gpio 9 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.9.4	root / gpio / physical / gpio 9 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.9.5	root / gpio / physical / gpio 9 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.9.6	root / gpio / physical / gpio 9 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.10.1	root / gpio / physical / gpio 10 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.1.10.2	root / gpio / physical / gpio 10 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.1.10.3	root / gpio / physical / gpio 10 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.10.4	root / gpio / physical / gpio 10 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.10.5	root / gpio / physical / gpio 10 / input mode	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = latching 1 = momentary
1.5.1.10.6	root / gpio / physical / gpio 10 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.1.11.1	root / gpio / physical / relay 1 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.1.11.2	root / gpio / physical / relay 1 / active triggers	String [3]	Read [1]	UTF8	
1.5.1.11.3	root / gpio / physical / relay 1 / status	Boolean [4]	Read [1]	False BOOLEAN	
1.5.2.1.1	root / gpio / virtual / vgpio 1 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.1.2	root / gpio / virtual / vgpio 1 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.1.3	root / gpio / virtual / vgpio 1 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.1.4	root / gpio / virtual / vgpio 1 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.1.5	root / gpio / virtual / vgpio 1 / vgpio source	String [3]	Read / Write [3]	UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.2.1.6	root / gpio / virtual / vgpio 1 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.2.1	root / gpio / virtual / vgpio 2 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.2.2	root / gpio / virtual / vgpio 2 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.2.3	root / gpio / virtual / vgpio 2 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.2.4	root / gpio / virtual / vgpio 2 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.2.5	root / gpio / virtual / vgpio 2 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.2.6	root / gpio / virtual / vgpio 2 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.3.1	root / gpio / virtual / vgpio 3 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.3.2	root / gpio / virtual / vgpio 3 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.3.3	root / gpio / virtual / vgpio 3 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.3.4	root / gpio / virtual / vgpio 3 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.3.5	root / gpio / virtual / vgpio 3 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.3.6	root / gpio / virtual / vgpio 3 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.4.1	root / gpio / virtual / vgpio 4 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.4.2	root / gpio / virtual / vgpio 4 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.4.3	root / gpio / virtual / vgpio 4 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.4.4	root / gpio / virtual / vgpio 4 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.4.5	root / gpio / virtual / vgpio 4 / vgpio source	String [3]	Read / Write [3]	UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.2.4.6	root / gpio / virtual / vgpio 4 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.5.1	root / gpio / virtual / vgpio 5 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.5.2	root / gpio / virtual / vgpio 5 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.5.3	root / gpio / virtual / vgpio 5 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.5.4	root / gpio / virtual / vgpio 5 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.5.5	root / gpio / virtual / vgpio 5 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.5.6	root / gpio / virtual / vgpio 5 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.6.1	root / gpio / virtual / vgpio 6 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.6.2	root / gpio / virtual / vgpio 6 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.6.3	root / gpio / virtual / vgpio 6 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.6.4	root / gpio / virtual / vgpio 6 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.6.5	root / gpio / virtual / vgpio 6 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.6.6	root / gpio / virtual / vgpio 6 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.7.1	root / gpio / virtual / vgpio 7 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.7.2	root / gpio / virtual / vgpio 7 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.7.3	root / gpio / virtual / vgpio 7 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.7.4	root / gpio / virtual / vgpio 7 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.7.5	root / gpio / virtual / vgpio 7 / vgpio source	String [3]	Read / Write [3]	UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.2.7.6	root / gpio / virtual / vgpio 7 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.8.1	root / gpio / virtual / vgpio 8 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.8.2	root / gpio / virtual / vgpio 8 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.8.3	root / gpio / virtual / vgpio 8 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.8.4	root / gpio / virtual / vgpio 8 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.8.5	root / gpio / virtual / vgpio 8 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.8.6	root / gpio / virtual / vgpio 8 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.9.1	root / gpio / virtual / vgpio 9 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.9.2	root / gpio / virtual / vgpio 9 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.9.3	root / gpio / virtual / vgpio 9 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.9.4	root / gpio / virtual / vgpio 9 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.9.5	root / gpio / virtual / vgpio 9 / vgpio source	String [3]	Read / Write [3]	UTF8	
1.5.2.9.6	root / gpio / virtual / vgpio 9 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.2.10.1	root / gpio / virtual / vgpio 10 / type	Integer [1]	Read / Write [3]	0 INTEGER	Allowed values 0 = disabled 1 = input 2 = output
1.5.2.10.2	root / gpio / virtual / vgpio 10 / input functions	String [3]	Read / Write [3]	UTF8	
1.5.2.10.3	root / gpio / virtual / vgpio 10 / output triggers	String [3]	Read / Write [3]	UTF8	
1.5.2.10.4	root / gpio / virtual / vgpio 10 / active triggers	String [3]	Read [1]	UTF8	
1.5.2.10.5	root / gpio / virtual / vgpio 10 / vgpio source	String [3]	Read / Write [3]	UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.2.10.6	root / gpio / virtual / vgpio 10 / status	Boolean [4]	Read / Write [3]	False BOOLEAN	
1.5.3.1	root / gpio / handlers / h-0	String [3]	Read [1]	LS Mute UTF8	
1.5.4.1	root / gpio / triggers / t-0	String [3]	Read [1]	Eth Link Down UTF8	
1.5.4.2	root / gpio / triggers / t-1	String [3]	Read [1]	AoIP Link Down UTF8	
1.5.4.3	root / gpio / triggers / t-2	String [3]	Read [1]	AC Power Off UTF8	
1.5.4.4	root / gpio / triggers / t-3	String [3]	Read [1]	DC Power Off UTF8	
1.5.4.5	root / gpio / triggers / t-4	String [3]	Read [1]	PTP Sync Lost UTF8	
1.5.4.6	root / gpio / triggers / t-5	String [3]	Read [1]	GPI 1 UTF8	
1.5.4.7	root / gpio / triggers / t-6	String [3]	Read [1]	GPI 2 UTF8	
1.5.4.8	root / gpio / triggers / t-7	String [3]	Read [1]	GPI 3 UTF8	
1.5.4.9	root / gpio / triggers / t-8	String [3]	Read [1]	GPI 4 UTF8	
1.5.4.10	root / gpio / triggers / t-9	String [3]	Read [1]	GPI 5 UTF8	
1.5.4.11	root / gpio / triggers / t-10	String [3]	Read [1]	GPI 6 UTF8	
1.5.4.12	root / gpio / triggers / t-11	String [3]	Read [1]	GPI 7 UTF8	
1.5.4.13	root / gpio / triggers / t-12	String [3]	Read [1]	GPI 8 UTF8	
1.5.4.14	root / gpio / triggers / t-13	String [3]	Read [1]	GPI 9 UTF8	
1.5.4.15	root / gpio / triggers / t-14	String [3]	Read [1]	GPI 10 UTF8	
1.5.4.16	root / gpio / triggers / t-15	String [3]	Read [1]	vGPI 1 UTF8	
1.5.4.17	root / gpio / triggers / t-16	String [3]	Read [1]	vGPI 2 UTF8	
1.5.4.18	root / gpio / triggers / t-17	String [3]	Read [1]	vGPI 3 UTF8	
1.5.4.19	root / gpio / triggers / t-18	String [3]	Read [1]	vGPI 4 UTF8	
1.5.4.20	root / gpio / triggers / t-19	String [3]	Read [1]	vGPI 5 UTF8	
1.5.4.21	root / gpio / triggers / t-20	String [3]	Read [1]	vGPI 6 UTF8	
1.5.4.22	root / gpio / triggers / t-21	String [3]	Read [1]	vGPI 7 UTF8	
1.5.4.23	root / gpio / triggers / t-22	String [3]	Read [1]	vGPI 8 UTF8	

OID / Path	Name path	Type	Access	Example value	Range / Enumeration
1.5.4.24	root / gpio / triggers / t-23	String [3]	Read [1]	vGPI 9 UTF8	
1.5.4.25	root / gpio / triggers / t-24	String [3]	Read [1]	vGPI 10 UTF8	
1.5.4.26	root / gpio / triggers / t-25	String [3]	Read [1]	LS Mute UTF8	

Functions

OID / Path	Name path	Description
1.2.1	root / system / reboot	Save configuration and reboot the unit

Matrices

OID / Path	Name path	Targets	Sources	Addressing	Parameters location	Labels	Description
1.4.3	root / audio routing / matrix	52	11	1	1.4.2 RELATIVE-OID	Primary: 1.4.1	Matrix to store audio connection info

Node index

OID / Path	Name path	Description
1	root	
1.1	root / identity	
1.2	root / system	
1.3	root / network	
1.3.2	root / network / eth0	eth0
1.3.3	root / network / eth1	eth1
1.4	root / audio routing	
1.4.1	root / audio routing / labels	
1.4.1.1	root / audio routing / labels / targets	
1.4.1.2	root / audio routing / labels / sources	
1.4.2	root / audio routing / parameters	
1.4.2.1	root / audio routing / parameters / targets	
1.4.2.1.0	root / audio routing / parameters / targets / t-0	
1.4.2.1.1	root / audio routing / parameters / targets / t-1	
1.4.2.1.2	root / audio routing / parameters / targets / t-2	
1.4.2.1.3	root / audio routing / parameters / targets / t-3	
1.4.2.1.4	root / audio routing / parameters / targets / t-4	
1.4.2.1.5	root / audio routing / parameters / targets / t-5	
1.4.2.1.6	root / audio routing / parameters / targets / t-6	
1.4.2.1.7	root / audio routing / parameters / targets / t-7	

OID / Path	Name path	Description
1.4.2.1.8	root / audio routing / parameters / targets / t-8	
1.4.2.1.9	root / audio routing / parameters / targets / t-9	
1.4.2.1.10	root / audio routing / parameters / targets / t-10	
1.4.2.1.11	root / audio routing / parameters / targets / t-11	
1.4.2.1.12	root / audio routing / parameters / targets / t-12	
1.4.2.1.13	root / audio routing / parameters / targets / t-13	
1.4.2.1.14	root / audio routing / parameters / targets / t-14	
1.4.2.1.15	root / audio routing / parameters / targets / t-15	
1.4.2.1.16	root / audio routing / parameters / targets / t-16	
1.4.2.1.17	root / audio routing / parameters / targets / t-17	
1.4.2.1.18	root / audio routing / parameters / targets / t-18	
1.4.2.1.19	root / audio routing / parameters / targets / t-19	
1.4.2.1.20	root / audio routing / parameters / targets / t-20	
1.4.2.1.21	root / audio routing / parameters / targets / t-21	
1.4.2.1.22	root / audio routing / parameters / targets / t-22	
1.4.2.1.23	root / audio routing / parameters / targets / t-23	
1.4.2.1.24	root / audio routing / parameters / targets / t-24	
1.4.2.1.25	root / audio routing / parameters / targets / t-25	
1.4.2.1.26	root / audio routing / parameters / targets / t-26	
1.4.2.1.27	root / audio routing / parameters / targets / t-27	
1.4.2.1.28	root / audio routing / parameters / targets / t-28	
1.4.2.1.29	root / audio routing / parameters / targets / t-29	
1.4.2.1.30	root / audio routing / parameters / targets / t-30	
1.4.2.1.31	root / audio routing / parameters / targets / t-31	
1.4.2.1.32	root / audio routing / parameters / targets / t-32	
1.4.2.1.33	root / audio routing / parameters / targets / t-33	

OID / Path	Name path	Description
1.4.2.1.34	root / audio routing / parameters / targets / t-34	
1.4.2.1.35	root / audio routing / parameters / targets / t-35	
1.4.2.1.36	root / audio routing / parameters / targets / t-36	
1.4.2.1.37	root / audio routing / parameters / targets / t-37	
1.4.2.1.38	root / audio routing / parameters / targets / t-38	
1.4.2.1.39	root / audio routing / parameters / targets / t-39	
1.4.2.1.40	root / audio routing / parameters / targets / t-40	
1.4.2.1.41	root / audio routing / parameters / targets / t-41	
1.4.2.1.42	root / audio routing / parameters / targets / t-42	
1.4.2.1.43	root / audio routing / parameters / targets / t-43	
1.4.2.1.44	root / audio routing / parameters / targets / t-44	
1.4.2.1.45	root / audio routing / parameters / targets / t-45	
1.4.2.1.46	root / audio routing / parameters / targets / t-46	
1.4.2.1.47	root / audio routing / parameters / targets / t-47	
1.4.2.1.48	root / audio routing / parameters / targets / t-48	
1.4.2.1.49	root / audio routing / parameters / targets / t-49	
1.4.2.1.50	root / audio routing / parameters / targets / t-50	
1.4.2.1.51	root / audio routing / parameters / targets / t-51	
1.4.2.2	root / audio routing / parameters / sources	
1.4.2.2.0	root / audio routing / parameters / sources / s-0	
1.4.2.2.1	root / audio routing / parameters / sources / s-1	
1.4.2.2.2	root / audio routing / parameters / sources / s-2	
1.4.2.2.3	root / audio routing / parameters / sources / s-3	
1.4.2.2.4	root / audio routing / parameters / sources / s-4	
1.4.2.2.5	root / audio routing / parameters / sources / s-5	
1.4.2.2.6	root / audio routing / parameters / sources / s-6	
1.4.2.2.7	root / audio routing / parameters / sources / s-7	
1.4.2.2.8	root / audio routing / parameters / sources / s-8	
1.4.2.2.9	root / audio routing / parameters / sources / s-9	
1.4.2.2.10	root / audio routing / parameters / sources / s-10	

OID / Path	Name path	Description
1.4.2.3	root / audio routing / parameters / connections	
1.4.2.3.0	root / audio routing / parameters / connections / t-0	
1.4.2.3.1	root / audio routing / parameters / connections / t-1	
1.4.2.3.2	root / audio routing / parameters / connections / t-2	
1.4.2.3.3	root / audio routing / parameters / connections / t-3	
1.4.2.3.4	root / audio routing / parameters / connections / t-4	
1.4.2.3.5	root / audio routing / parameters / connections / t-5	
1.4.2.3.6	root / audio routing / parameters / connections / t-6	
1.4.2.3.7	root / audio routing / parameters / connections / t-7	
1.4.2.3.8	root / audio routing / parameters / connections / t-8	
1.4.2.3.9	root / audio routing / parameters / connections / t-9	
1.4.2.3.10	root / audio routing / parameters / connections / t-10	
1.4.2.3.11	root / audio routing / parameters / connections / t-11	
1.4.2.3.12	root / audio routing / parameters / connections / t-12	
1.4.2.3.13	root / audio routing / parameters / connections / t-13	
1.4.2.3.14	root / audio routing / parameters / connections / t-14	
1.4.2.3.15	root / audio routing / parameters / connections / t-15	
1.4.2.3.16	root / audio routing / parameters / connections / t-16	
1.4.2.3.17	root / audio routing / parameters / connections / t-17	
1.4.2.3.18	root / audio routing / parameters / connections / t-18	
1.4.2.3.19	root / audio routing / parameters / connections / t-19	
1.4.2.3.20	root / audio routing / parameters / connections / t-20	
1.4.2.3.21	root / audio routing / parameters / connections / t-21	
1.4.2.3.22	root / audio routing / parameters / connections / t-22	
1.4.2.3.23	root / audio routing / parameters / connections / t-23	
1.4.2.3.24	root / audio routing / parameters / connections / t-24	

OID / Path	Name path	Description
1.4.2.3.25	root / audio routing / parameters / connections / t-25	
1.4.2.3.26	root / audio routing / parameters / connections / t-26	
1.4.2.3.27	root / audio routing / parameters / connections / t-27	
1.4.2.3.28	root / audio routing / parameters / connections / t-28	
1.4.2.3.29	root / audio routing / parameters / connections / t-29	
1.4.2.3.30	root / audio routing / parameters / connections / t-30	
1.4.2.3.31	root / audio routing / parameters / connections / t-31	
1.4.2.3.32	root / audio routing / parameters / connections / t-32	
1.4.2.3.33	root / audio routing / parameters / connections / t-33	
1.4.2.3.34	root / audio routing / parameters / connections / t-34	
1.4.2.3.35	root / audio routing / parameters / connections / t-35	
1.4.2.3.36	root / audio routing / parameters / connections / t-36	
1.4.2.3.37	root / audio routing / parameters / connections / t-37	
1.4.2.3.38	root / audio routing / parameters / connections / t-38	
1.4.2.3.39	root / audio routing / parameters / connections / t-39	
1.4.2.3.40	root / audio routing / parameters / connections / t-40	
1.4.2.3.41	root / audio routing / parameters / connections / t-41	
1.4.2.3.42	root / audio routing / parameters / connections / t-42	
1.4.2.3.43	root / audio routing / parameters / connections / t-43	
1.4.2.3.44	root / audio routing / parameters / connections / t-44	
1.4.2.3.45	root / audio routing / parameters / connections / t-45	
1.4.2.3.46	root / audio routing / parameters / connections / t-46	
1.4.2.3.47	root / audio routing / parameters / connections / t-47	
1.4.2.3.48	root / audio routing / parameters / connections / t-48	
1.4.2.3.49	root / audio routing / parameters / connections / t-49	

OID / Path	Name path	Description
1.4.2.3.50	root / audio routing / parameters / connections / t-50	
1.4.2.3.51	root / audio routing / parameters / connections / t-51	
1.4.2.3.51.0	root / audio routing / parameters / connections / t-51 / s-0	
1.5	root / gpio	
1.5.1	root / gpio / physical	
1.5.1.1	root / gpio / physical / gpio 1	
1.5.1.2	root / gpio / physical / gpio 2	
1.5.1.3	root / gpio / physical / gpio 3	
1.5.1.4	root / gpio / physical / gpio 4	
1.5.1.5	root / gpio / physical / gpio 5	
1.5.1.6	root / gpio / physical / gpio 6	
1.5.1.7	root / gpio / physical / gpio 7	
1.5.1.8	root / gpio / physical / gpio 8	
1.5.1.9	root / gpio / physical / gpio 9	
1.5.1.10	root / gpio / physical / gpio 10	
1.5.1.11	root / gpio / physical / relay 1	
1.5.2	root / gpio / virtual	
1.5.2.1	root / gpio / virtual / vgpio 1	
1.5.2.2	root / gpio / virtual / vgpio 2	
1.5.2.3	root / gpio / virtual / vgpio 3	
1.5.2.4	root / gpio / virtual / vgpio 4	
1.5.2.5	root / gpio / virtual / vgpio 5	
1.5.2.6	root / gpio / virtual / vgpio 6	
1.5.2.7	root / gpio / virtual / vgpio 7	
1.5.2.8	root / gpio / virtual / vgpio 8	
1.5.2.9	root / gpio / virtual / vgpio 9	
1.5.2.10	root / gpio / virtual / vgpio 10	
1.5.3	root / gpio / handlers	
1.5.4	root / gpio / triggers	
1.5.5	root / gpio / vgpio sources	